

M1300(2-PACK)

Cudy M1300(2-Pack) AC1200 Wi-Fi Gigabit Mesh Solution



Specifications

Model	M1300(2-Pack)
Brand	Cudy
WIFI	WiFi5
Geni?lik	Dual band
Mesh	Mesh
Tezlik	2.4Ghz/5Ghz
Qo?ulma say?	100+

KEY FEATURES

Model	M1300	
Hardware Features	Processor	Dual-Core Processors
	Flash	128Mbit (16MB)
	DDR	1Gbit (128MB)
	Antenna	2 × Internal Omni-Directional Antennas
	Interface	1 × 1000/100/10 Mbps WAN Port 1 × 1000/100/10 Mbps LAN Port
	Button	Pair Button, Reset Button
	External Power Supply	12V/1A
Wireless Features	Wireless Standards	IEEE 802.11/ac/n/a 5GHz IEEE 802.11/n/b/g 2.4GHz
	Frequency	5GHz, 2.4GHz
	Signal Rate	867Mbps (5GHz),300Mbps (2.4GHz) Compatible with 802.11a/b/g/n/ac Wi-Fi standards
	Transmit Power	CE: <20dBm (2.4GHz), <23dBm (5.15GHz~5.25GHz) FCC: <30dBm (2.4GHz & 5.15GHz~5.825GHz)
	Wireless Modes	Enable/Disable Wireless Radio, WMM
	Wireless Security	WEP, WPA/WPA2, WPA-PSK/WPA2-PSK
Software Features	WAN Type	Dynamic IP/Static IP/PPPoE
	DHCP	Server, DHCP Client List, Address Reservation
	Dynamic DNS	Compatible with 15 more DDNS providers
	Guest Network	2.4GHz guest network × 1 5GHz guest network × 1
	NAT	Port Forwarding, Port Triggering, UPnP, DMZ
	VPN Client	PPTP/L2TP/OpenVPN/WireGuard/IPSec/Zerotier
Others	Package Contents	2-Pack AC1200 Wi-Fi Mesh Router Power Adapter RJ45 Ethernet Cable Quick Installation Guide
	System Requirements	Microsoft Windows 98SE/NT/2000/XP/Vista™/7/8/8.1/10, MAC OS, NetWare, UNIX or Linux Firefox 12.0, Chrome 20.0, Safari 4.0, or other Java-enabled browsers Cable or DSL Modem Subscription with an internet service provider (for internet access)