

# M1800 (1-Pack)

Cudy M1800(1-Pack) AX1800 Wi-Fi 6 Mesh Solution



Model	M1800 (1-Pack)
Brend	Cudy
WIFI	WiFi6
Genişlik	Dual band
Mesh	Mesh
Tezlik	2.4Ghz/5Ghz
Qoşulma sayı	100+

## Specification

Model	M1800	
Hardware Features	Processor	Dual-Core Processors
	Flash	128Mbit (16MB)
	DDR	2Gbit (256MB)
	Antenna	4 × Internal Omni-Directional Antennas
	Interface	1 × 1000/100/10Mbps WAN Port
		1 × 1000/100/10Mbps LAN Port
	Button	Pair Button, Reset Button
External Power Supply	12V/1A	
Wireless Features	Wireless Standards	IEEE 802.11ax/ac/n/a 5GHz
		IEEE 802.11ax/n/b/g 2.4GHz
	Frequency	5GHz, 2.4GHz
	Signal Rate	1201Mbps (5GHz), 574Mbps (2.4GHz)
		Compatible with 802.11a/b/g/n/ac/ax Wi-Fi standards
	Transmit Power	CE: <20dBm (2.4GHz), <23dBm (5.15GHz~5.25GHz)
		FCC: <30dBm(2.4GHz & 5.15GHz~5.825GHz)
Wireless Modes	Enable/Disable Wireless Radio, WMM	
Wireless Security	WEP, WPA/WPA2, WPA-PSK/WPA2-PSK, WPA3	
Software Features	WAN Type	Dynamic IP/Static IP/PPPoE
	DHCP	Server, DHCP Client List, Address Reservation
	Dynamic DNS	Compatible with 15 more DDNS providers

Guest Network	2.4GHz guest network × 1	
	5GHz guest network × 1	
NAT	Port Forwarding, Port Triggering, UPnP, DMZ	
VPN	PPTP/L2TP/OpenVPN/WireGuard/IPSec/Zerotier	
Others	Package Contents	2-Pack AX1800 Wi-Fi 6 Mesh Router
		Power Adapter
		RJ45 Ethernet Cable
		Quick Installation Guide
	System Requirements	Microsoft Windows 98SE/NT/2000/XP/Vista™/7/8/8.1/10, MAC OS, NetWare, UNIX or Linux
		Firefox 12.0, Chrome 20.0, Safari 4.0, or other Java-enabled browsers
		Cable or DSL Modem
		Subscription with an internet service provider (for internet access)