

M3000(2-Pack)

Cudy M3000(2-Pack) AX3000 Wi-Fi 6 Mesh 2.5G Solution



Model	M3000(2-Pack)
Brend	Cudy
WIFI	WiFi6
Genişlik	Dual band
Mesh	Mesh
Tezlik	2.4Ghz/5Ghz
Qoşulma sayı	250+

Specification

Model	M3000	
Hardware Features	Processor	1.3GHz Dual Core Cortex-A53 Processor
	Flash	1Gbit (128MB)
	DDR	2Gbit (256MB)
	Antenna	5 × Internal Omni-Directional Antennas
	Interface	1 × 2.5Gbps WAN Port
		1 × 10/100/1000 Mbps LAN Port
	Button	Pair Button, Reset Button
External Power Supply	12V/1A	
Wireless Features	Wireless Standards	IEEE 802.11ax/ac/n/a 5GHz
		IEEE 802.11ax/n/b/g 2.4GHz
	Frequency	5GHz, 2.4GHz
	Wireless Bandwidth	20/40/80/160MHz
	Signal Rate	2402Mbps (5GHz), 574Mbps (2.4GHz)
		Compatible with 802.11a/b/g/n/ac/ax Wi-Fi standards
	Transmit Power	CE: <20dBm (2.4GHz), <23dBm (5GHz)
		FCC:<30dBm (2.4GHz & 5GHz)
	Wireless Modes	Enable/Disable Wireless Radio, WMM
Wireless Security	WEP, WPA/WPA2, WPA-PSK/WPA2-PSK, WPA3	
Wireless Features	OFDMA, MU-MIMO, Beamforming	
Software Features	WAN Type	Dynamic IP/Static IP/PPPoE
	DHCP	Server, DHCP Client List, Address Reservation
	Dynamic DNS	Compatible with 15 more DDNS providers
	Guest Network	2.4GHz guest network × 1
		5GHz guest network × 1
	NAT	Port Forwarding, Port Triggering, UPnP, DMZ

VPN Client	PPTP/L2TP/OpenVPN/WireGuard/IPsec	
Others	Package Contents	2-Pack AX3000 Wi-Fi Mesh Router
		Power Adapter
		RJ45 Ethernet Cable
		Quick Installation Guide
	System Requirements	Microsoft Windows 98SE/NT/2000/XP/Vista™/7/8/8.1/10, MAC OS, NetWare, UNIX or Linux
		Firefox 12.0, Chrome 20.0, Safari 4.0, or other Java-enabled browser
		Cable or DSL Modem
		Subscription with an internet service provider (for internet access)