

# MP35UB

DSPPA - MP35UB - 35W Mini Digital Mixer Amplifier with USB & Bluetooth (1.5U)



## Specifications

Model	MP35UB
Brand	Dsppa
Watt	35W

KEY FEATURES

<b>Model</b>	<b>MP35UB</b>
<b>Power Supply</b>	<b>~110-240 50/60Hz</b>
<b>MIC1 Input Sensitivity</b>	<b>5.5mV±1mV</b>
<b>MIC2 Input Sensitivity</b>	<b>5.5mV±1mV</b>
<b>AUX1 Input Sensitivity</b>	<b>350mV±10%</b>
<b>AUX2 Input Sensitivity</b>	<b>350mV±10%</b>
<b>EMC Input Sensitivity</b>	<b>350mV±10%</b>
<b>MIC Frequency Response</b>	<b>200Hz~10kHz (±3dB)</b>
<b>AUX Frequency Response</b>	<b>100Hz~15kHz (±3dB)</b>
<b>Noise</b>	<b>&lt;5mV (4Ω load out)</b>
<b>Distortion</b>	<b>&lt;1% 1KHZ</b>
<b>Treble Adjustment</b>	<b>10dB (±2)</b>
<b>Bass Adjustment</b>	<b>10dB (±2)</b>
<b>RatedOutput Power</b>	<b>35W</b>
<b>Interface OutputMode</b>	<b>70V, 100V (constant voltage output), 4-16Ω</b>
<b>Machine Size (D×W×H)</b>	<b>198×247×66mm</b>
<b>Package Size</b>	<b>302×343×121mm (1PC)</b>
<b>Maximum Package Size</b>	<b>355×630×283mm (4PCS)</b>
<b>Net Weight</b>	<b>2.55kg</b>
<b>Gross Weight</b>	<b>3.2kg (1PC)</b>