

SENSEFACE 2A KIT

ZKTECO SENSEFACE 2A KIT (TLEB102 Exit Button + LM-2805 Electromagnetic Lock), hər hansı bir standart qapını ağıllı və təhlükəsiz keçid nöqtəsinə çevirmək üçün lazım olan 3 əsas komponenti ehtiva edir. Sistemin beyni olan SenseFace 2A, ZKTeco-nun qabaqcıl "Visible Light" (Görünən Işıq) texnologiyası ilə təchiz olunmuş, işçilərin üzünü, RFID kartını və ya şifrəsini oxuyaraq qapını açan terminaldır. Otaqdan çıxarkən qapını açmaq üçün TLEB102 Təmassız (No-Touch) infraqırmızı düyməsinə sadəcə əlinizi yaxınlaşdırmağınız kifayətdir. Qapının fiziki olaraq bağlı qalmasını isə paketə daxil olan güclü LM-2805 Elektromaqnit Kilidi (280 kq dözümlülük) təmin edir.



Specifications

Model	SenseFace 2A Kit
Brand	ZKTeco
Cihaz tipi	Controller
Kart tipi	IC
Qo?ulma	Wifi
Barmaq izi	3000
Kart say?	3000

KEY FEATURES

Feature	Details
Display	2.4-inch Touch Screen (Toxunmalı Ekran)
Face Capacity	1,500 (Visible Light Recognition)
Card Capacity	3,000 (ID / IC Card support)
Log Capacity	100,000 Records
Verification Speed	< 0.3 seconds
Communication	TCP/IP, USB-Host, Wi-Fi
Access Control Interfaces	Electric Lock, Door Sensor, Exit Button, Alarm
Lock Type	Electromagnetic Lock (Maqnit Kilid)
Holding Force	280 kg (600 lbs)
Voltage	DC 12V / 24V
Material	Anodized Aluminum Housing
Suitable Door Types	Wooden, Glass, Metal, Fireproof Doors
Button Type	No-Touch / Touchless Infrared Sensor
Material	Stainless Steel Panel (Paslanmaz Polad)
Detection Range	0.1 ~ 10 cm
LED Indicator	Blue (Standby) / Green or Red (Active)
Output Contact	NO / NC / COM